

ZK-TB22 50W*2+100W TWS 真无线 TPA3126D2 2.1 声道蓝牙音频功放模块

Wuzhi Audio APP 下载二维码

Wuzhi Audio APP download



ZK-TB22

全芯设计 · 对箱功能

2.1声道蓝牙音频功放板



2颗 TPA3116D2

- ✓ 立体声和低音炮音量分别调节
- ✓ 支持远程固件更新
- ✓ 加大电容加大散热片

赠送:炫酷APP
外壳需自己组装


目录

ZK-TB22 50W*2+100W TWS 真无线 TPA3116D2 2.1 声道 蓝牙音频功放模块.....	1
目录.....	2
产品亮点	3
旋钮介绍	4
短接输出低音加重.....	5
功能介绍	6
固件更新	7
对箱功能	8
产品参数	9
安装示意图及包装清单	10
APP 设置界面	11

1. 产品亮点

产品亮点

储能电容: 4700ufx2+470uf电容容量更大, 声音更结实



薄膜电容
滤波效果更好,
安静无杂音,
波形还原度
更好

**全新蓝牙
解码芯片**
解析更好

加大散热片
散热效果好


2. 旋钮介绍

旋钮介绍



3. 短接输出低音加重

短接输出低音加重



短接S1和S2
立体声输出低音加重



出厂默认非短接，为正常模式，立体声输出不含200Hz以下低音部分。

如果想要立体声输出低音加重，输出全频，需要短接S1两个焊盘，以及S2两个焊盘。

4. 功能介绍

功能介绍



5. 固件更新

APP功能全面

改蓝牙名称

可更改每个产品的蓝牙名称，多个产品轻松识别。

改蓝牙密码

可修改蓝牙连接密码，防止别人劫持。
此功能可关闭。

调提示音大小

可调节提示音音量的大小，满足客户不同需求。

开/关提示音

提示音可选择开启或者关闭。



固件更新

6. 对箱功能

对箱功能

TWS互联

两台功放一起用




对箱功能操作介绍

- 1 打开两台同型号功放。
- 2 任意选择一台功放，向里三连击带按键功能的总音量旋钮，此时红色TWS指示灯闪烁，另外一台功放与其自动配对为立体声组合。（如果15秒内没有配对成功，会自动取消对箱配对模式，您可再次三连击按键尝试一次）
- 3 如果配对成功，选择的那一台会被分配为左声道，红色指示灯常亮，另一台为右声道，红色指示灯慢闪。
- 4 下次开机，会自动找到对箱。如果想取消对箱模式，只需要选择一台功放，三连击按键即可。

7. 产品参数


产品参数



品牌：Wuzhi Audio
型号：ZK-TB22
名称：2.1声道50W+50W+100W高音低音炮调节蓝牙音频功率放大器
功放芯片：TPA3116D2
蓝牙版本：5.1
蓝牙传输距离：10米(如需更远距离，请自行接外置天线)
音频输入：蓝牙+AUX
音频输出：左声道50W+右声道50W+低音炮100W
适配电源：DC12-24V， $\geq 7A$ (不可接交流电)
适配喇叭：左右声道20-50W，4-8 Ω ；低音炮20-100W，4-8 Ω
音量调节：总音量、立体声音量、低音炮音量分别调节，调节范围广； 总音量带按键 单击：播放/暂停 双击：下一曲 三击：选择或取消对箱模式
保护机制：过温，过流，短路，防静电保护
特色功能：支持Wuzhi Audio APP。修改蓝牙名称，密码设置，提示音音量调节，开/关提示音，助眠曲，固件升级，等等。 对箱功能，真无线功能使两套音箱可以组合成为左右声道对箱，空间定位感更强。
产品尺寸：121x100x26mm
产品重量：净重215g，含包装258g

8. 安装示意图及包装清单

安装示意图及包装清单



赠送:



9. APP 设置界面

APP设置界面



蓝牙名称修改步骤

【输入新蓝牙名称】→【点设置按钮】→系统自动重启→【手机蓝牙取消与原蓝牙名称配对】→【找到新蓝牙名称重新配对】

蓝牙密码设置步骤

方法一：

【打开蓝牙密码开关】→使用默认密码 1111

方法二：

【打开蓝牙密码开关】→【输入密码】→【点设置按钮】→系统自动重启→【取消配对，再次连接会提示输入密码】

ZK-TB22 50W*2+100W TWS true wireless TPA3126D2 2.1 channel BT audio amplifier module

ZK-TB22

Full core design • Box matching function
2.1 channels BT audio amplifier board



2 TPA3116D2
pcs

- ✓ Stereo and subwoofer volume are adjusted separately
- ✓ Support remote firmware update
- ✓ Large capacitance and large heat sink

Free:Cool APP

The shell needs to be assembled by yourself


Catalogue

ZK-TB22 50W*2+100W TWS true wireless TPA3126D2 2.1 channel BT audio amplifier module	12
Catalogue	13
Product highlights	14
Knob introduction	15
Short circuit output bass emphasis	16
Function introduction	17
Firmware update	18
Box matching function	19
Product parameters.....	20
Installation diagram.....	21
APP setting interface.....	22

1. Product highlights

Product highlights

Energy storage capacitor: 4700ufx2 + 470uf capacitance is larger and sound is stronger



Thin film capacitor
Better filtering effect, quiet without noise, better waveform restoration

New BT decoding chip
Better parsing

Larger heat sink
Good heat dissipation effect


2. Knob introduction

Knob introduction



3. Short circuit output bass emphasis

Short circuit output bass emphasis




Short circuit S1 and S2
stereo output Bass
emphasis

The factory default is not short circuited, which is the normal mode. The stereo output does not include the bass part below 200Hz.

If you want stereo output bass emphasis and full frequency output, you need to short connect two pads S1 and two pads S2.

4. Function introduction

Function introduction



5. Firmware update

APP Comprehensive functions

Change BT name

The BT name of each product can be changed, and multiple products can be easily identified.

Change BT password

The BT connection password can be modified to prevent others from hijacking. This function can be turned off.

Adjust the volume of prompt tone

The volume of prompt tone can be adjusted to meet different needs of customers.

ON / OFF prompt tone

The prompt tone can be turned on or off.




Firmware Update

6. Box matching function

Box matching function

TWS interconnection

Two power amplifiers are used together




Introduction to box matching function and operation

- 1** Turn on two power amplifiers of the same model.
- 2** Select a power amplifier at will, and press the total volume knob with key function inwards three times. At this time, the red TWS indicator flashes, and the other power amplifier is automatically paired with it as a stereo combination. (if the pairing is not successful within 15 seconds, the pairing mode will be canceled automatically. You can try again by pressing the key three times.)
- 3** If the pairing is successful, the selected one will be assigned to the left channel, and the red indicator will always be on. The other one is the right channel, and the red indicator will flash slowly.
- 4** The next time you start the machine, you will automatically find the right box. If you want to cancel the box matching mode, you only need to select a power amplifier and press the button three times.

7. Product parameters

Product parameters



Brand: Wuzhi Audio

Model: ZK-TB22

Name: 2.1 channel 50W x2+100W treble and subwoofer BT audio power amplifier

Amplifier chip: TPA3116D2

BT version: 5.1

BT transmission distance: 10m (if you need more distance, please connect external antenna by yourself)

Audio input: BT+AUX

Audio output: Left & Right channel 50W + Subwoofer 100W

Adaptive power supply: DC12-24V, $\geq 7A$ (Do not connect to AC)

Adaptive speaker: Left & Right channel 20-50W, 4-8 Ω ;
Subwoofer 20-100W, 4-8 Ω

Volume control: The total volume, stereo volume and subwoofer volume are adjusted separately, with a wide range of adjustment;
Total volume (with buttons) Click: play/pause
Double click: next Three Click: select or cancel the box matching mode


Protection mechanism: Over temperature, over-current, short circuit, anti-static protection

Characteristic function: Support Wuzhi audio app. Modify BT name, password setting, volume adjustment of prompt tone, on/off prompt tone, sleep music, firmware upgrade, etc.
Box matching function, the true wireless function enables the two sets of speakers to be combined into left and right channel boxes, with a stronger sense of spatial positioning.

Size: 121x100x26mm

Product weight: Net weight 215g, Weight with package 258g

8. Installation diagram



9. APP Setting interface

APP Setting interface



BT name modification steps

[enter a new BT name] → [click set button] → [system automatic restart] → [cancel pairing of mobile BT with the original BT name] → [find a new BTname and re pair]

BT password setting steps

Method 1:

[turn on BT password switch] → Use default password 1111

Method 2:

[turn on BT password switch] → [enter password] → [click the setting button] → [the system will restart automatically] → [cancel pairing, and you will be prompted to enter password when connecting again]